

SURI PENDANT INSTALLATION INSTRUCTIONS

These instructions are provided for your safety.

Please read carefully before commencing work and retain for future reference.

SAFETY INFORMATION

- * If you are in any doubt consult a person competent to give advice on the installation of electrical equipment.
- * This fitting should be fitted in accordance with IEE Wiring Regulations and the Building Regulations
- * To prevent electrocution switch off at the mains supply before installing or maintaining this fitting. Ensure other persons cannot restore the electricity supply without your knowledge.
- * To avoid damage to concealed wiring during installation, establish the direction of the supply cable before drilling fixing holes.
- * This fitting is Class 2 =□ therefore no earth is required and should be fitted to a lighting supply protected by a 5 amp fuse or equivalent circuit breaker.
- * Always be sure to use the correct type and wattage of bulbs as indicated on the fitting. Never exceed the wattage stated.
- * When changing the bulb, always switch off at the mains and allow the old bulb to cool down before handling. Dispose of used bulbs carefully.

INSTALLATION

It is possible to adjust the length of the chain at this point. Using 2 pairs of pliers with a soft cloth between the jaws open up a link in the chain. Open up another link to remove the length of chain required and then close the links back up. Pull the excess cable up through the ceiling cup leaving the cable slightly slack through the chain. **Ensure that it is the chain supporting the weight of the fitting and not the cable.**

1. Ensure the house electricity supply is off at the fuse board.
2. If you are fitting this product in place of an existing one, you may find that there are more than 3 sets of cables connected. If there are loop in cables that are not connected to the light these must be terminated in a separate terminal block not connected to the fitting. Before removing existing fitting, carefully note position of each set of cables
3. If there are loop in cables that are not connected to the light these must be terminated in a separate terminal block not connected to the fitting.
4. Remove the mounting bracket from the fitting by undoing the screws located on the sides of the ceiling cup
5. Using the mounting bracket as a template mark and drill holes in the ceiling ensuring that they are into a joist or other suitable mounting. Fix the mounting bracket to ceiling with suitable fixings. **Take care not to damage wiring.**
6. Use a screwdriver to lever open the connector block housing and feed supply cable through rubber sleeve. The weight of the fitting must be supported whilst making the electrical connections as follows:
Connect the supply live (normally brown or red) to fitting live (marked "L") on the terminal block.
Connect the supply neutral (normally blue or black) to fitting neutral (marked "N") on the terminal block.
Please note: No earth should be connected to any part of this fitting. If an earth is present please terminate these in a separate terminal block (not supplied) to ensure that continuity is maintained for the earth circuit.
Snap connector cover closed ensuring that the connections are sound and no loose strands of wire are exposed.
7. Attach fitting to the mounting bracket by using any screws and washers that were removed earlier. **Take care not to trap any wiring in the process.**
8. **Fit the bulb**, type and wattage as indicated on the fitting. **The wattage indicated must not be exceeded.**
9. Reattach any droppers that may have come loose during transit. Please ensure that all droppers are securely attached.
10. Switch on the electricity supply at the fuse board.

GENERAL INFORMATION

This fitting is designed for internal use only and must be fitted to a DRY SURFACE as any dampness in plaster or paint can damage the finish. **Do not use polish or abrasive cleaner - just a soft dry cloth.**

