

BUREAU WALL LIGHT INSTALLATION INSTRUCTIONS

These instructions are provided for your safety.

Please read them carefully before commencing work and retain them for future reference.

SAFETY INFORMATION

- * If you are in any doubt consult a person competent to give advice on the installation of electrical equipment.
- * This fitting should be fitted in accordance with IEE Wiring Regulations and the Building Regulations
- * To prevent electrocution switch off at the mains supply before installing or maintaining this fitting. Ensure other persons cannot restore the electricity supply without your knowledge.
- * To avoid damage to concealed wiring during installation, establish the direction of the supply cable before drilling fixing holes.
- * This fitting is Class 1 = $\frac{1}{\text{E}}$ and should be fitted to a lighting supply (with earth) protected by a 5 amp fuse or equivalent circuit breaker.
- * Always be sure to use the correct type and wattage of bulbs as indicated on the fitting. Never exceed the wattage stated.
- * When changing the bulb, always switch off at the mains and allow the old bulb to cool down before handling. Dispose of used bulbs carefully.

INSTALLATION

1. Ensure the house electricity supply is off at the fuse board.
2. If you are fitting this unit in place of an existing fitting, you may find that there are more than 3 sets of cables connected within the rose. Before removing the existing rose, carefully note the position of each set of cables. If there are loop in cables that are not connected to the light these must be terminated in a separate terminal block not connected to the fitting.
3. Remove the mounting bracket from the fitting by undoing the screws on the side of the rose and retain screws.
4. Attach the mounting bracket to the wall using suitable fixings. Ensure the screws are firmly fixed into a suitable mounting and not just the plaster.
5. The weight of the fitting must be supported whilst you make the electrical connections.
Connect the supply live (normally brown or red) to fitting live (marked "L") on the terminal block.
Connect the supply neutral (normally blue or black) to fitting neutral (marked "N") on the terminal block.
Connect the supply earth (normally green/yellow or unsheathed) to earth (marked " $\frac{1}{\text{E}}$ ") on terminal block.
NOTE: Ensure electrical connections are tight and no loose strands of wire are left out of the terminal block.
6. Move any excess cable into wall void and care must be taken to prevent any excess cable obstructing the switch or the pull cord.
7. Fix the fitting to the mounting bracket using the screws removed earlier. **Take care not to damage wiring.**
8. Remove the shade ring from fitting then fit the glass shade followed by the shade ring. Align the glass shade then secure with shade tool.
9. Fit the bulb type and wattage as indicated on the fitting.
10. Switch on the electricity supply at the fuse board.

GENERAL INFORMATION

This fitting is designed for internal use only and must be fitted to a DRY SURFACE as any dampness in plaster or paint can damage the finish. **Do not use polish or abrasive cleaner - just a soft dry cloth.**